



CORNELIUS SYSTEMS

info@mycornelius.com
877.545.5558
MyCornelius.com
1302 Anderson Rd
Clawson, MI 48017



GLORY MACH 3

Coin Sorter / Counter

The Mach 3 significantly reduces the time required by your staff to count and sort coin. Counting and sorting at up to 1,500 coins per minute, the Mach 3 accelerates coin processing increasing accuracy and efficiency. Its compact size means it can be easily stored when not in use and transported between different locations. By automating coin processing, you can release employees to focus on revenue generating and customer facing activities and reduce errors while simultaneously increasing their job satisfaction.

● **Fast and Flexible**

Sorts and counts coins at 1,500 coins per minute, and can be configured to capture coins in regular or mega coin drawers, coin bags, or pre-formed paper coin rolls. When equipped with an optional printer, receipts can be issued with all coin transactions.

● **Simplicity**

Simple and easy to use - the keypad offers full travel keys and convenient left or right hand access. Operation itself is highly intuitive, offering a simplified, keyboard and control with two levels of totals, batch and grand. Tutorial prompting guides the operator through every process using an easy to read LCD display.

● **Low Staff Impact**

The MACH 3 uses Glory's patented Figure 8 design, which is highly impervious to coin jams resulting from bent or mutilated coins or non-coin debris often mixed in with the coins. In the case of a coin jam, recovery is also simple and fast.

● **Dimensions (H x W x D)**

9.25" x 9" x 15.4"

● **Weight**

16.8 lbs

● **Tilting Inspection Pan**

1,500 coins

● **Speed**

1,500 coins

● **Security**

Lock out security feature
Battery backup for power failures
Optional batch remote display

● **Compact Design**

Compact and portable - the base model occupies only about 1 square foot of counter space and weighs-in at less than 17 lbs. It also features a built-in convenient carry handle and an attractive appearance that complements any décor.

